

# Quick Guide

## 2757 IP Phone





1. Msg. Wait Light	10. Soft Key	19. Speed Dial Key
2. LCD Display	11. Menu Key	20. Speed Dial Key
3. Line Key	12. Nav. Key	21. 12 Number Keys
4. Line Key	13. Message Key	22. Headset Key
5. Line Key	14. Select Key	23. Mute Key
6. Line Key	15. DND Key	24. Speaker Key
7. Soft Key	16. Speed Dial Key	25. Speaker
8. Soft Key	17. Speed Dial Key	26. Volume Key
9. Soft Key	18. Speed Dial Key	







## Package Contents

Thank you for purchasing the 2757 IP Phone. Please check the package contents before you start to use the phone. If any item is missing, please contact your dealer.



1	IP Phone
2	Handset
3	Handset Cord
4	AC Adapter (Optional)
5	Network Cable
6	Desk Stand
7	Quick Start Guide

## Installation Instructions

	
<p>Connect the network cable to the network port (left) on the back of the 2757. You may optionally connect a computer to the network port on the right.</p>	<p>Install the desk stand as shown in the picture above</p>
	
<p>Connect the handset cord to the handset.</p>	<p>Connect the other end of the handset cord to the handset port on the base of the 2757.</p>
	
<p>If you are not using Power over Ethernet (PoE), plug the AC adapter into an electrical outlet.</p>	<p>Connect the power plug of the AC adapter to the phone as shown above.</p>

You should now see some text displayed on the LCD screen.

## Network Setup (PPPoE/DHCP)

If you are using PPPoE (frequently used with ADSL) or DHCP (frequently used with cable internet), please follow the steps below.

1. Press MENU key to enter setup menu. Then press UP/DOWN to select 3. Settings. Press SELECT Key.

03:12 09/09	0123456		
1. Phone Book			
2. Call Records			
3. Settings			
Select		Exit	

2. Press UP/DOWN to select 4. System Configuration. Press SELECT Key.

03:12 09/09	0123456		
1. Language			
2. Ring Type			
3. Contrast			
4. System Configuration			
Select		Exit	

3. Press UP/DOWN to select 1. Network Setting. Press UP/DOWN key until PPPoE or DHCP is highlighted. Press SAVE. If DHCP is selected, skip to Step 6.

03:12 09/09	0123456		
1. Network Setting			
PPPoE			
2. IP Address (Static)			
192.168.4.50			
Select		Exit	

4. If using PPPoE, press UP/DOWN until 7. PPPoE Username is highlighted. Press SELECT and use the keypad to enter the username. Use CLEAR to delete. Press SAVE to store the username.

03:12 09/09	0123456		
6. DNS Server2 (Static)			
168.95.1.1			
2. PPPoE Username			
Alan			
Save	Clear	Cancel	

5. Press UP/DOWN until 8. PPPoE Password is highlighted. Press SELECT and enter the PPPoE password with the keypad. Then press SAVE.

03:12 09/09	0123456		
7. PPPoE Username			
Alan			
8. PPPoE Password			
Alan123			
Save	Clear	Cancel	

6. Press UP/DOWN until 10. SIP Proxy is highlighted. Press SELECT and use the keypad to enter the IP address. Use \* for the dot. Press SAVE to store proxy address.

03:12 09/09	0123456		
10. SIP Proxy			
192.168.4.2			
11. SIP PortNum			
5060			
Save	Clear	Cancel	

7. Press UP/DOWN key to select 11. SIP Port Num. Press SELECT then use the keypad to enter the SIP Port Number (usually 5060).

03:12 09/09	0123456		
10. SIP Proxy	192.168.4.2		
11. SIP PortNum	5060 ■		
Save	Clear	Cancel	

8. Press UP/DOWN until 12. SIP Username is highlighted. Press SELECT and enter the SIP Username with the keypad. Press SAVE.

03:12 09/09	0123456		
12. SIP Username	0123456 ■		
13. SIP Phone Num	0123456		
Save	Clear	Cancel	

9. Press UP/DOWN key to select 13. SIP Phone Num. Press SELECT then use the keypad to enter the SIP Phone Number.

03:12 09/09	0123456		
12. SIP Username	0123456		
13. SIP Phone Num	0123456 ■		
Save	Clear	Cancel	

10. Press UP/DOWN until 14. SIP Password is highlighted. Press SELECT and enter the SIP password with the keypad. Then press SAVE.

03:12 09/09	0123456		
14. SIP Password	1234567890 ■		
15. Codec	2. Auto-G.711u		
Save	Clear	Cancel	

11. Press UP/DOWN until 16. Commit Changes is highlighted. Press SELECT to save the changes.

03:12 09/09	0123456		
15. Codec	2. Auto-G.711u		
16. Commit Changes	Changes saved		
Select		Exit	

12. Press UP/DOWN until 17. Reboot is highlighted. Press SELECT to reboot the phone. A reboot can take up to 1 minute.

03:12 09/09	0123456		
16. Commit Changes	Changes saved		
17. Rebooting	.....		
Select		Exit	

13. When VoIP SIP PHONE is displayed on the LCD screen, the setup procedure is completed.

03:12 09/09	0123456		
VoIP SIP Phone			
Redial			